



Product Information

- Applications:** Accent, Linear, Cove, Undercounter
- Volts:** 12V
- Lamps:** Incandescent or LEDs
- Lamp Life:** See Lamp Specifications
- Socket:** Custom
- Extrusion:** White Plastic V-Reflector

Indoor Applications

- Amusement Industries**
Night Clubs, Movie Theatres
- Recreation Industries**
Hotels, Restaurants, Casinos
- Architectural Industries**
Interior Decor, Shopping Centers
- Construction Industries**

Lamp Specifications

Catalog #	Description	Volts	Watts	Lamp Life Hrs.	Max. Lamps Per Run	4" O/C	6" O/C	12" O/C	18" O/C
IN-A	.33 Watt Incandescent	12	.33	80,000	500	166'	250'	500'	750'
IN-B	.86 Watt Incandescent	12	.86	90,000	209	69'	104'	209'	313'
LED-A	LED Amber	12	.20	100,000	1000	333'	500'	500'	500'
LED-BA	LED Bright Amber	12	.45	100,000	260	86'	130'	260'	390'
LED-Y	LED Yellow	12	.20	100,000	1000	333'	500'	500'	500'
LED-BY	LED Bright Yellow	12	.45	100,000	260	86'	130'	260'	390'
LED-R	LED Red	12	.20	100,000	1000	333'	500'	500'	500'
LED-BR	LED Bright Red	12	.45	100,000	260	86'	130'	260'	390'
LED-G	LED Green	12	.20	100,000	1000	333'	500'	500'	500'
LED-BG	LED Bright Green	12	.45	100,000	260	86'	130'	260'	390'

Specifier: _____

Series /Lens/Spacing/Lamp

Product Code: LPL8300 / * C / _____ / _____

Project: _____

Type: _____

Date: _____

* Note: Lens is Clear

Application and Construction

Designed to utilize Light Emitting Diodes (LEDs) or incandescent lamps, LipLite provides many desirable features. Of primary importance the long life of the LEDs makes it an excellent product to reduce maintenance in the future. LEDs also consume 1/3 less wattage than incandescent bulbs.

LipLite can be easily field cut for an easy and fast installation not requiring exact field dimensions. AisleLite is excellent to illuminate undercounters, shelves, or any area that requires a soft glow of light. LipLite can also be used as linear or accent lighting. Suggested spacing is 2" or 3" on center for even illumination and 12" on center for accent or linear light.

Electrical

LipLite is supplied with a 120V (primary side)/12V (secondary side) transformer. Specify other primary side voltage if different than 120V. LipLite runs at 12V. Terminal Breaker Box is used for secondary protection.

Material: White 14 Gage Flat Conductor.