



**Product Information**

**Applications:** Cove, Linear or Point/Spot Lighting  
**Volts:** 24V (12V Available Upon Request)  
**Lamps:** Festoon 3W, 5W or 10W (Included)  
**Lamp Life:** See Lamp Specifications  
**Socket:** Clear Custom  
**Optional:** MR8, MR11, MR16 Lamps

**Indoor Applications**

- Amusement Industries**  
Night Clubs, Movie Theatres
- Recreation Industries**  
Hotels, Restaurants, Casinos
- Architectural Industries**  
Interior Decor, Shopping Centers
- Construction Industries**

**Lamp Specifications**

Catalog #	Description	Volts	Watts	Lamp Life Hrs.	Max. Lamps Per Run	2" O/C	3" O/C	4" O/C	6" O/C
3WIN	3 Watt Incandescent	24	3	8,000	160	26'	40'	53'	80'
5WIN	5 Watt Incandescent	24	5	8,000	144	24'	36'	48'	72'
10WIN	10 Watt Incandescent	24	10	8,000	72	12'	18'	24'	36'
3WXE	3 Watt Xenon	24	3	10,000	160	26'	40'	53'	80'
5WXE	5 Watt Xenon	24	5	15,000	144	24'	36'	48'	72'
10WXE	10 Watt Xenon	24	10	10,000	72	12'	18'	24'	36'

**Specifier:** \_\_\_\_\_

**Product Code:** **Series/Spacing/ Lamp / Mounting**  
 FL4000/ \_\_\_\_\_ / \_\_\_\_\_ / \_\_\_\_\_

**Project:** \_\_\_\_\_

**Type:** \_\_\_\_\_

**Date:** \_\_\_\_\_

**Application and Construction**

Designed to utilize festoon lamps, FestLite provides many desirable features. Of primary importance the option of incandescent lamps for a warm color or xenon lamps for a whiter color for your indirect lighting needs. Easy lamp replacement makes an excellent product to reduce maintenance in the future.

**Electrical**

FestLite has the option of being mounted with easy to install mounting clips, u-channel, or v-reflector. FestLite can be easily field cut for an easy and fast installation not requiring exact field dimensions. FestLite is excellent to illuminate areas for cove lighting or indirect lighting. Suggested spacing is 3"-4" for scallop free cove lighting.

**Application and Construction**

FestLite is supplied with a 120V (primary side)/24V (secondary side) transformer. Specify other primary side voltage if different than 120V. FestLite runs at 24V. FestLite is a 20 amp system (12 gage wire).

**Optional Accessories**

Lens cover for v-reflector, halogen sockets (MR8, MR11, MR16).